

Connecting cord for power supply Connecting cord for controller Power cord relay for leg massage

1. Cord arrangement of the connecting cord for power supply, connecting cord for controller and power cord relay for leg massage.

*The three types of wires are to be arranged with the massage block set in its upper most position (in respect to the chair).

1. Set the 3 types of connectors, (a), (b), and (c) in the circuitry of the massage block.
2. Install the ground wires (d) and (e).
3. Arrange the wires in the cord guides so that they do not lift out, then fix the cords using the metal fasteners.
4. Install the massage block cover, and attach the cord using the massage block cover clips.
5. Wind the cord around the chair-side cord wire one time.
6. Attach the cord to the side surface of the frame (f) using an insulated tie.
7. Band the cord together in the positions shown in the photo with insulated ties.

***Caution during installation.**

- Put the massage block at its upper most point.
- Do not allow the cord to ride on top of the frame (f).

