


Trouble shooting



No operation when pressing any pad of controller.

Check the massage block operation.


Press the test switch of the main circuit board, and check the massage block operation.

• Operation test method

- 1 Turn on the power switch.
- 2 Press the stop switch to turn off.
- 3 Press the test switch for more than 1 second.

• Caution

When returning to normal operation, turn off the power switch and check that the controller lamp turned off. Then turn the power switch on again.





• Contents of test operation

- [1] Position the massage wheel to the weakest position.
 - [2] Move the massage block to the center of the up/down stroke.
 - [3] Massage upward 3 times.
 - [4] Start rolling up.
 - [5] Stop at back position and position the massage wheel to the strongest and the weakest position.
 - [6] Start tapping rolling up to the selected shoulder position and turn down.
 - [7] Move down to the lowest position and turn up.
 - [8] Move the massage block up to the center of the up/down stroke under massage rolling mode.
 - [9] Move to reset position.
- *Reset position means that the massage wheel stops at weakest and widest position.

OK

- If a problem remains even after completing all operations, it is possible that the problem is with the connecting cord for the controller (disconnected), controller cord (disconnected), or with the controller itself.
- In the case of a problem with one of the clutches or detectors, if during operations [1] ~ [9], if one operation continues and does not move on to the next operation, in the case of a operation other than kneading, the operation will exceed its limit and will lock. Check parts related to the operation in which the lock occurred, or in the proceeding operation. In the case of locking during kneading, the locked state will repeat.





*Refer to connecting diagram on the page 8 for Ground location.